

EngyVolt RV15

Multifunctional Electrical Energy Counter

For measuring voltage, frequency, current, power, as well as active and reactive power

- ◆ In low-voltage systems with a maximum nominal voltage of 500 V L-L (289 V L/N)
- ◆ In single-phase and three-phase power systems with 3 or 4 wires

Operation:

4 button on site at the front side of the multifunctional measuring device



Input:

- ◆ AC 110 - 400 V +/- 10%
(110 - 300 V for installations acc. to UL)
- ◆ DC 120 - 350 V +/-20%
(120 - 300 V for installations acc. to UL)

Output:

- MODBUS RTU (RS485)
- Pulse output (optional for RV15)